

## Z-VAT-DC / CL-6

### DC bipolar voltage detector

Network Type : MV-LV

#### Application:

- Bipolar DC voltage detector: 100 to 30,000 V DC.
- The low threshold, set at 100 V, detects any voltage exceeding the Very Low Voltage DC limits.
- Indoor use (to be used only on laboratory and workshop type installations).
- Presence of voltage indicated by the lighting up of 6 red LEDs and the emission of an audible signal.
- Function control of the integrated device which validates all detector functions. :
  - Contact the handle's magnetic shoe with the rail and shunt the assembly by making contact between the magnetic handle and the contact hook;
  - Press the test button: 6 red LEDs light up, audible signal sounds;
  - Release the test button: momentary illumination of the 6 green LEDs.



#### Features:

Presence of voltage indicated by:

- 6 red LEDs light up,
- Sound signal (60 dB (A)/2 m)
- 380 mm contact electrode
- Overall detector length: 840 mm.
- Indication group: III

#### Composition:

- 2 elements with removable antennae, connected by a 1.9 m cable.
- 1 carrying case.



Référence

**CL-6-100/30000**

Weight (kg)

4,300